

Motor Protection Circuit Breaker and Motor Circuit Protector Specifications

Bulletin Number 140M

Topic	Page
Bulletin 140M Motor Protection Circuit Breakers	3
Overview	3
Catalog Number Explanation	5
Application Diagrams	6
Bulletin 140M Motor Circuit Protectors	9
Overview	9
Catalog Number Explanation	10
Application Diagrams	11
Specifications	13
Application Ratings	13
Definition of Type 2 Short Circuit Coordination:	19
Specifications	22
Cutoff Current	33
Approximate Dimensions	39

Summary of Changes

This publication updates current rating information beginning on [page 22](#).

Additional Resources

These documents contain additional information concerning related products from Rockwell Automation.

Resource	Description
Use of Motor Protection Circuit Breakers with Variable-Frequency Drives, publication 140M-AT002	Provides application information about using 140M devices with variable-frequency drives.
Industrial Automation Wiring and Grounding Guidelines, publication 1770-4.1	Provides general guidelines for installing a Rockwell Automation industrial system.
Product Certifications website, http://www.ab.com	Provides declarations of conformity, certificates, and other certification details.

You can view or download publications at <http://www.rockwellautomation.com/literature/>. To order paper copies of technical documentation, contact your local Allen-Bradley distributor or Rockwell Automation sales representative.

LISTEN.
THINK.
SOLVE.

Notes:



Bulletin 140M Motor Protection Circuit Breakers

Overview

Motor Protection Circuit Breakers may provide the following protective and control functions.

- Disconnect for Motor Branch Circuit
- Branch-Circuit, Short-Circuit Protection (Magnetic Protection)
- Overload Protection (Thermal Protection)
- Switching (Manual)

In North America, electrical codes require that an individual Motor Branch Circuit be protected by a UL/CSA Listed Fuse, Circuit Breaker or Self-Protected Combination Motor Controller.

140M-C, D, and F Frames

The 140M-C, D, and F frame Motor Protection Circuit Breakers may have two cULus Listings - as Manual, Self-Protected Combination Motor Controllers and as Manual Motor Controllers (with optional approvals for Motor Disconnect and Group Installation). Cat. No. 140M-D8V* can also be applied at the output of a variable frequency drive (VFD) in multi-motor applications.

When UL/CSA listed as Manual, Self-Protected Combination Motor Controllers, the 140M Motor Protection Circuit Breakers provide all of the necessary NEC/CEC requirements for the protection and control of individual Motor Branch Circuits without additional protective devices.

At some higher voltages and currents (particularly at 600V), a few of the 140M-C, D, and F frame devices are only UL/CSA Listed as Manual Motor Controllers (with optional approvals for Motor Disconnect and Group Installation). In NEC/CEC Group Installations, these devices must be applied per the appropriate rules which require the use of an upstream Branch-Circuit, Short-Circuit Protective Device (BCPD).

Standards Compliance and Certifications

Standards Compliance	Certifications
IEC/EN60947-1,-2,-4-1,-5-1	CE Marked
IEC/EN60204-1	CCC
CSA,C22.2 No.14	CSA Certified
UL508	cULus Listed (File No. E54612, NLRV(7); E205542, NKJH(7); E197878, DIVQ(7);)
	ATEX