SIEMENS



Figure similar

Data sheet for SIMOTICS M-1PH8

Article No. : **1PH8163-1DD10-1BB1**

Client order no. :
Order no. :
Offer no. :
Remarks :

Item no. :
Consignment no. :
Project :

Engineering data

		P_N [kW]	M_N [Nm]	I_N [A]	U_N [V]	f_N [Hz]	n_N [rpm]	M_{max} [Nm]	I_{max} [A]	n_{max} [rpm]	M_0 [Nm]	I_0 [A]	η	cos φ	Iμ [A]
Y	**ALM 400V**	**25.0**	**208.0**	**55.0**	**343**	**39.2**	**1,150**	**600**	**151.0**	**6,500**	**248.0**	**61**	**0.915**	**0.880**	**17.5**
	BLM/SLM 400V	22.0	210.0	55.0	300	34.2	1,000	600	151.0	6,500	248.0	61	0.909	0.890	17.3
	ALM 480V	31.0	197.0	52.0	442	50.9	1,500	600	151.0	6,500	248.0	61	0.930	0.880	17.7
	BLM/SLM 480V	28.0	198.0	52.0	400	45.8	1,350	600	151.0	6,500	248.0	61	0.924	0.880	17.7

Mechanical data

Motor type	Squirrel cage asynchronous motor
Shaft height	160
Cooling	Forced ventilation NDE -> DE
Vibration severity grade	R/A
Shaft and flange accuracy	R
Degree of protection	IP55
Design acc. to Code I	IM B3 (IM V5, IM V6, IM B6, IM B7, IM B8)
Temperature monitoring	Pt1000 temperature sensor in the stator winding
Color	Standard (Anthracite RAL 7016)
Type of the bearing	Standard with fixed bearing
Shaft end	Feather key with full key balancing
Encoder system	Incremental encoder 22 bit with commutation position 11 bit, max. encoder speed = 12000 rpm

Physical constants

Thermal time constant	35 min
Moment of inertia	2,160 kgcm²
Weight (approx.)	196 kg

Connection

Type of electrical connection	Terminal box
Position of the connection	NDE top
Power connection	left
Signal connection	DE
Terminal box designation	gk863

Cooling data and sound pressure level

Airflow, min.	0.16 m³/s
Sound pressure level LpA(1m) motor + external fan operation 50 HZ rated load, tolerance + 3dB	73 dB [1)]
Air discharge	axial
Pressure drop	200 Pa

External fan

Max. power consumption

3 AC 400 V / 50 Hz (±10%)	0.16 A
3 AC 400 V / 60 Hz (±10%)	0.21 A
3 AC 480 V / 60 Hz (±10%)	0.21 A

[1)] at a rated frequency of 4 kHz and a speed range of up to 5000 rpm

Siemens 1PH81631DD101BB1 Motors and Motor Control | gesrepair.com